

Elegant and stylish, this three-button option allows the user to select the most appropriate choice to meet their needs.

The first button sends a signal to the waiter's pager, the second button is to cancel the call, and the third button is used to request a bill (adjustable to suit your requirements). The button also has LED illumination along the perimeter.



## Specifications

General	
Frequency	434.6500 MHz
Frequency Stability	+/- 10 ppm
Data Rate	1800 bps
Channel Space	12.5 KHz
Modulation	FSK (+/- 3KHz)
Antenna	PCB type
Output Power(Max.)	10 mW
Power Supply	Coin Battery CR2032 X 2
Indicator(audio)	No sound
Indicator(video)	2 LEDs (call indicator)
Size(mm)	74 X 46 X 11
Weight(g)	28
Installation Method	Both-sided Tape

## Features

Multi-button available (till 3)

Function selectable: Call only or Call & Cancel

Dual indicator LEDs

Maximized battery life time

## Call Systems Technology Ltd

Unit 240, Centennial Park, Elstree, Hertfordshire, WD6 3SJ

Registered address: 50 Seymour Street, London W1H 7JG

Registered in England No. 4025235 • VAT Reg. No. GB 220 8954 10

Stay connected:

